

1.	<b>Serien Nr. / Series No.</b>	<b>AFFC</b>
2.	<b>Raster / Pitch:</b>	<b>x</b>
3.	<b>Polzahl / Number of Conduct</b>	<b>xx</b>
4.	<b>Material: Kupfer Leitung Größe Material: Copper Conductor Size</b>	<b>xx</b>
5.	<b>Anschlusstyp / Terminal Types :</b>	<b>xx</b>
6.	<b>Gesamtlänge / Overall Length (mm)</b>	<b>xxx</b>

### 1: Serien Nr. / Series No.

### 2: Raster / Pitch:

X	Raster / Pitch (mm)	Länge der Abisolierung* / Strip length* (mm)	Länge der Unterstützungstreifen* / Support tape length* (mm)
A	2.54	5.00	10.00
B	1.25	5.00	10.00
C	1.00	5.00	10.00
D	0.80	4.00	8.00
E	0.50	4.00	8.00





\*Max. Länge der Unterstützungstreifen: 20,00mm  
Max. support tape length: 20.00mm

### 3: Polzahl / Number of Conduct: 04 ~ 32

### 4: Material: Kupfer Leitung Größe Copper Conductor Size

xx	Größe / Size	Raster / Pitch	mm
	Dicke / Thickness	Breite / Width	
01	0.1	1.27	2.54
02	0.1	0.8	1.25
03	0.05	0.8	1.25
04	0.1	0.7	1.00
05	0.05	0.7	1.00
06	0.035	0.7	1.00
07	0.1	0.5	0.80
08	0.05	0.3	0.50
09	0.035	0.3	0.50
10	0.035	0.8	1.25
11	0.05	0.6	1.00
12	0.1	0.3	0.80

### 5: Anschlusstyp / Terminal Types :

xx	Typ / Type
T1	
T2	
T7	
T9	

\* Mindestbestellmenge: 5000 Stk (Standard)  
\* Minimum order quantity: 5000 pcs (Standard)

Serien Nr. / Series No.	Raster / Pitch:	Polzahl / Number of Conduct	Kupfer Leitung Größe Copper Conductor Size	Anschlusstyp / Terminal Types	Gesamtlänge / Overall Length (mm)
1	2	3	4	5	6
AFFC	x	xx	xx	xx	xxx